

# LT-8

## Fluoropolymer Nano-coating

### Technical Data Sheet

The LT-8 Nano-coating is a high-performance fluoropolymer dissolved in a non-flammable fluorinated solvent.

The LT-8 when applied to products exhibits superior hydrophobic (water repellent) and oleophobic (oil repellent) properties at a sub micron level.

Designed for protection of high quality products like printed circuit boards (PCBs), LT-8 will protect a board and the electronic components from moisture, water, condensation and corrosion.

LT-8 also excels in preventing damage from solvents and other chemicals.

The LT-8 material can be applied to printed circuit boards (PCBs) and other electronic devices without the need for masking when applied at 1-2 um film thickness.

The LT-8 coating can be applied via spray, dip or brush. The coating can be cured in air or accelerated via oven bake. The material can be supplied with a UV trace added to aid inspection.

## Features

- Highly repellent to liquid (hydrophobic) and oil (oleophobic)
- Resistant to solvents and chemicals
- Dries extremely quickly at room temperature
- Possible to apply coating without masking critical components
- Wide temperature range performance
- High dielectric strength material
- Easily inspected with a UV trace
- Products certified to IPX5, IPX7
- Easy to apply by spray and dip methods
- Customizable chemistry
- Survives Gamma and E-beam exposure

#### Copyright Thin Film Partners 2017

The information in this document is believed to be correct as of the date issued. Judgments as to the suitability of information herein for the purchaser's purposes are necessarily the purchaser's responsibility. Although reasonable care has been taken in the preparation of such information, Thin Film Partners, extends no warranties, makes no representations, and assumes no responsibility as to the accuracy or suitability of such information for application to the purchaser's intended purpose or for consequences of its use.

Thin Film Partners LLC  
2976 E. State Street #120-32  
Eagle, Idaho 83616

[www.thinfilmpartners.com](http://www.thinfilmpartners.com)  
Sales@thinfilmpartners.com



## Properties

<b>Liquid Properties</b>	Color and clarity:	Slightly cloudy to clear
	Odor:	Similar to ether
	Content/Concentration:	1.0- 2.0 wt%
	Viscosity:	Varies with concentration of solids
	Shelf Life At Room Temperature:	5 years in unopened container
	Solubility:	In fluorosolvents
	Flammability:	Non-flammable
	Environmental: Toxicity rating:	Low in toxicity, non-ozone depleting HMIS Rating Health = 1
<b>Electrical Properties</b>	Dielectric Breakdown Strength:	1000 V/mil
	Dielectric Constant [at 30% RH]:	3.0 (at 1 kHz)
	Dissipation Factor [at 30% RH]:	0.009 (at 1 kHz)
<b>Physical Performance</b>	Continuous operating temperature:	125°C
	Max heat (short term):	200°C
	Contact Angle (water):	115°-120° (on glass)
	Contact Angle (oil):	60° (on glass)
	Adhesion:	Excellent
<b>Application</b>	Ease of application:	Easy, no vacuum chamber required
	Mode of application:	Spray, dip, brush
<b>Work Schedule</b>	Dry to Touch:	10-20s
	Tack Free time:	30-45 minutes
	Recommended Dry time:	12 hours

### Copyright Thin Film Partners 2017

The information in this document is believed to be correct as of the date issued. Judgments as to the suitability of information herein for the purchaser's purposes are necessarily the purchaser's responsibility. Although reasonable care has been taken in the preparation of such information, Thin Film Partners, extends no warranties, makes no representations, and assumes no responsibility as to the accuracy or suitability of such information for application to the purchaser's intended purpose or for consequences of its use.

Thin Film Partners LLC  
2976 E. State Street #120-32  
Eagle, Idaho 83616

[www.thinfilmpartners.com](http://www.thinfilmpartners.com)  
Sales@thinfilmpartners.com



## **APPLICATION**

### **Cleaning**

In general all surfaces to be coated should be thoroughly cleaned before coating. This may be required to ensure that satisfactory adhesion to the substrate is possible.

### **Dip Coating**

Fluorinated solvent should be used to keep the LT-8 coating at a suitable viscosity for dipping.

Solvent is added periodically as the solvent evaporates. The viscosity should be checked using a viscosity meter or "flow cup" on a regular basis.

The product should be immersed in the LT-8 dipping tank in the vertical position, or at an angle as close to the vertical as possible. The product should then be withdrawn.

After withdrawing, the product should be left to drain over the tank until the majority of residual coating has left the surface.

### **Bulk Spraying**

LT-8 does not need to be thinned before spraying.

If the bulk coating material has been agitated, allow to rest until air bubbles have dispersed.

LT-8 is suitable both for use in manual spray guns and selective spray equipment.

A good technique is to hold the gun at 45 degrees angle and a distance of approximately 20-25cm while spraying. Spray a thin and continuous film onto the product with an even motion. Turn the circuit 90 degrees and repeat the process. Rotate a full 360 degrees to cover all sides of the product.

This process helps to ensure penetration of the coating beneath the components and in confined spaces.

### **Aerosol Spraying**

Avoid shaking the can before use. This may add excessive bubbles and give a poorer finish.

A good technique is to hold the aerosol can at 45 degrees angle and a distance of approximately 20-25cm while spraying. Spray a thin and continuous film onto the product with an even motion. Turn the product 90 degrees and repeat the process. Rotate a full 360 degrees to cover all sides of the product.

This process helps to ensure penetration of the coating beneath the components and in confined spaces.

#### **Copyright Thin Film Partners 2017**

The information in this document is believed to be correct as of the date issued. Judgments as to the suitability of information herein for the purchaser's purposes are necessarily the purchaser's responsibility. Although reasonable care has been taken in the preparation of such information, Thin Film Partners, extends no warranties, makes no representations, and assumes no responsibility as to the accuracy or suitability of such information for application to the purchaser's intended purpose or for consequences of its use.

Thin Film Partners LLC  
2976 E. State Street #120-32  
Eagle, Idaho 83616

[www.thinfilmpartners.com](http://www.thinfilmpartners.com)  
[Sales@thinfilmpartners.com](mailto:Sales@thinfilmpartners.com)



**Brushing**

The coating should be kept at ambient temperature. Gently apply the coating with a good quality brush so as not to leave brush marks and so that the components and wiring are not disturbed.

**Drying times & curing conditions**

LT-8 will be touch dry in 10-20 seconds at room temperature and does not require a thermal cure.

The full properties of LT-8 will be obtained after 12 hours at room temperature.

**Coating removal & repair**

LT-8 can be easily removed using fluorinated solvents, which can be locally or completely stripped depending on requirements. Removal can be achieved using a cotton bud, brush or complete immersion in a bath of the stripper.

Compatibility of the fluorinated solvents with the PCB should be assessed at all times.

**Inspection**

The LT-8 coating can be supplied with a UV trace within the coating itself, which fluoresces under UV light.

This aids inspection of the material after drying and during coating application. Suitable lighting includes UVA.

**Applications**

The LT-8 coating is used in almost all industrial sectors.

They include:

- Aviation
- Aerospace
- Defense
- Automotive
- Industrial
- Oil & Gas
- Electronics
- Medical/Pharmaceutical
- Optics
- Telecommunications
- White goods / Commercial

This list is limited and there are a lot more areas that they are used.

**Copyright Thin Film Partners 2017**

The information in this document is believed to be correct as of the date issued. Judgments as to the suitability of information herein for the purchaser's purposes are necessarily the purchaser's responsibility. Although reasonable care has been taken in the preparation of such information, Thin Film Partners, extends no warranties, makes no representations, and assumes no responsibility as to the accuracy or suitability of such information for application to the purchaser's intended purpose or for consequences of its use.

Thin Film Partners LLC  
2976 E. State Street #120-32  
Eagle, Idaho 83616

[www.thinfilmpartners.com](http://www.thinfilmpartners.com)  
[Sales@thinfilmpartners.com](mailto:Sales@thinfilmpartners.com)